


535T



Open, Close & Stop Transmitter to Control 27 Doors. Match dipswitches 1 thru 5 on both transmitter and receiver. Set the 6th, 7th, & 8th dipswitch in open/close/stop receiver accordingly.

“Changes or modifications not expressly approved by the party responsible for compliance could void the user’s authority to operate the equipment”

Receiver	Dial Setting 1-9	Dial Setting ABC	6th Dipswitch on Receiver	7th Dipswitch on Receiver	8th dipswitch on Receiver
Door 1	1	A	“+”	“+”	“+”
Door 2	2	A	“+”	“+”	“O”
Door 3	3	A	“+”	“+”	“-”
Door 4	4	A	“+”	“O”	“+”
Door 5	5	A	“+”	“O”	“O”
Door 6	6	A	“+”	“O”	“-”
Door 7	7	A	“+”	“-”	“+”
Door 8	8	A	“+”	“-”	“O”
Door 9	9	A	“+”	“-”	“-”
Door 10	1	B	“O”	“+”	“+”
Door 11	2	B	“O”	“+”	“O”
Door 12	3	B	“O”	“+”	“-”
Door 13	4	B	“O”	“O”	“+”
Door 14	5	B	“O”	“O”	“O”
Door 15	6	B	“O”	“O”	“-”
Door 16	7	B	“O”	“-”	“+”
Door 17	8	B	“O”	“-”	“O”
Door 18	9	B	“O”	“-”	“-”
Door 19	1	C	“-”	“+”	“+”
Door 20	2	C	“-”	“+”	“O”
Door 21	3	C	“-”	“+”	“-”
Door 22	4	C	“-”	“O”	“+”
Door 23	5	C	“-”	“O”	“O”
Door 24	6	C	“-”	“O”	“-”
Door 25	7	C	“-”	“-”	“+”
Door 26	8	C	“-”	“-”	“O”
Door 27	9	C	“-”	“-”	“-”